

7. Electrical Parts List

7-1 .GXE1395/UCX

Loc No.	New Code No.	Old Code No.	Description	Specification	Remarks
ASSY-PCB,MAIN(COM)					
	● AA97-10031D		ASSY-PCB,MAIN(COM)	TXE1395/UCX,KG1,USA	
PCB	AA41-10472A	36029-0554-000	PCB-MAIN	KG1,1,FR-1,330X245X1.6T	BARE PCB
C/FBT	AA65-30002A	33333-0005-010	CLAMP-FBT	- ,NYLON-66,V0,BLK,-,-	
C/FBT	AA65-30009A	36633-101-911	CLAMP-FBT	- ,ABS,V0,BLK,-,-	
Cl 01	2202-000127	A1100-0803	C-CERAMIC,MLC-AXIAL	10NF,+80-20%,25V,Y5V,-,7J	
Cl 02	31607-402-220		C-ELECTROLYTIC	CE04W TAPG 50V 2.2M	
cl 04	2202-000127	A1100-0803	C-CERAMIC,MLC-AXIAL	10NF,+80-20%,25V,Y5V,-,7J	
Cl 07	2401-000832	31607-401-690	C-AL	220UF,20%,25V,GP,8X11MM,5	
Cl 08	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
Cl 09	2401-001530	31607-401-670	C-AL	47UF,20%,25V,GP,5X11MM,5M	
Cl 10	2401-000269	31607-401-470	C-AL	100UF,20%,16V,GP,6X11MM,5	
C151	2202-000173	A1100-0338	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,1.9X3.5MM	
C152	2202-000127	A1100-0803	C-CERAMIC,MLC-AXIAL	10NF,+80-20%,25V,Y5V,-,7J	
C153	2202-000127	A1100-0803	C-CERAMIC,MLC-AXIAL	10NF,+80-20%,25V,Y5V,-,7J	
C154	2202-000127	A1100-0803	C-CERAMIC,MLC-AXIAL	10NF,+80-20%,25V,Y5V,-,7J	
C201	2201-000292	31417-104-400	C-CERAMIC,DISC	1NF,10%,50V,Y5P,5*4,5MM,T	
C202	31607-402-200		C-ELECTROLYTIC	CE04W TAPG 50V 0.47M	
C203	2401-001495	31607-401-460	C-AL	47UF,20%,16V,GP,5X11MM,5M	
C204	2301-000201	31507-127-002	C-FILM,PEF	2.2NF,5%,50V,7.4X3.9X13MM	
C205	31607-402-200		C-ELECTROLYTIC	CE04W TAPG 50V 0.47M	
C206	2301-000224	31507-127-008	C-FILM,PEF	22NF,5%,50V,7.4X3.9X13MM	
C207	31607-402-200		C-ELECTROLYTIC	CE04W TAPG 50V 0.47M	
C209	2306-000122	B1102-0318	C-FILM,MPPF	100NF,5%,50V,7.3X4.0X5.0M	
C210	2306-000122	B1102-0318	C-FILM,MPPF	100NF,5%,50V,7.3X4.0X5.0M	
C211	2306-000122	B1102-0318	C-FILM,MPPF	100NF,5%,50V,7.3X4.0X5.0M	
C212	2202-000127	A1100-0803	C-CERAMIC,MLC-AXIAL	10NF,+80-20%,25V,Y5V,-,7J	
C213	2201-000193	31407-105-090	C-CERAMIC,DISC	10PF,0.25PF,50V,NPO,-,5MM	
C214	2401-000620	31607-402-580	C-AL	2.2UF,10%,50V,GP,5X11MM,5	
C215	2401-000269	31607-401-470	C-AL	100UF,20%,16V,GP,6X11MM,5	
C218	2301-000181	31507-127-018	C-FILM,PEF	18NF,5%,50V,7.1X3.5X13MM	
C219	2401-000620	31607-402-580	C-AL	2.2UF,10%,50V,GP,5X11MM,5	
C220	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C221	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C222	2306-000122	61102-0318	C-FILM,MPPF	100NF,5%,50V,7.3X4.0X5.0M	
C223	2201-000354	31407-057-200	C-CERAMIC,DISC	20PF,5%,50V,NPO,5.0*3.0,2	
C225	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C226	2401-000603	31607-402-210	C-AL	1UF,20%,50V,GP,5X11MM,5MM	
C227	2306-000122	B1102-0318	C-FILM,MPPF	100NF,5%,50V,7.3X4.0X5.0M	
C231	2401-001495	31607-401-460	C-AL	47UF,20%,16V,GP,5X11MM,5M	
C232	2401-000808	31607-401-480	C-AL	220UF,20%,16V,GP,8X11MM,5	
C234	2202-000279	A1100-0796	C-CERAMIC,MLC-AXIAL	47PF,5%,50V,SL,3.5X19MM,-	
C235	2202-000127	A1100-0803	C-CERAMIC,MLC-AXIAL	10NF,+80-20%,25V,Y5V,-,7J	
C236	2202-000127	A1100-0803	C-CERAMIC,MLC-AXIAL	10NF,+80-20%,25V,Y5V,-,7J	
C237	2202-000154	A1100-0799	C-CERAMIC,MLC-AXIAL	150PF,10%,50V,Y5P,-,-,TP	
C251	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C301	2301-000310	31507-127-011	C-FILM,PEF	68NF,5%,50V,8.0X8.5X4.0X5	
C302	2301-000226	31507-137-017	C-FILM,PEF	27NF,5%,100V,7.3X4X12.5MM	
C303	2201-000161	31417-109-140	C-CERAMIC,DISC	10NF,+80-20%,500V,Y5V,10X	
C304	2401-000553	31607-402-570	C-AL	1UF,10%,50V,GP,5X11MM,5MM	
C305	2305-000427	A1102-0299	C-FILM,MPEF	47NF,5%,100V,7.5X12.5X3.5	
C306	2401-000360	31607-402-290	C-AL	100UF,20%,50V,GP,8X11MM,5	
C307	2305-000470	A1102-0300	C-FILM,MPEF	68NF,5%,100V,-,5MM,TP	

Loc No	New Code No	Old Code No	Description	Specification	Remarks
C308	2201-000556	31417-106-090	C-CERAMIC,DISC	470PF,10%,500V,Y5P,6X3.5M	
C309	2401-000175	31607-402-710	C-AL	1000UF,20%,35V,GP,13X25MM	
C310	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C311	31607-402-200		C-ELECTROLYTIC	CE04M TAPG 50V 0.47M	
C312	2401-000553	31607-402-570	C - A L	1UF,10%,50V,GP,5X11MM,5MM	
△ C401	2401-000148	31507-137-013	C-FILM,PEF	10NF,5%,100V,7X3.2X7MM,5M	
C402	A1102-0205		C-FILM	ff 922 P 1.6KV T 632-J BU	
C403	2201-000467	31417-767-331	C-CERAMIC,DISC	330PF,10%,2KV,Y5P,-,5MM,T	
△ C404	2306-000184	31517-333-334	C-FILM,MPPF	330nF,5%,250V,-,7.5mm,TP	
△ C405	2305-000154	31517-003-020	C-FILM,MPEF	100NF,5%,400V,21.5X6.5X11	
C406	2201-000556	31417-106-090	C-CERAMIC,DISC	470PF,10%,500V,Y5P,6X3.5M	
△ C407	2401-001397	A1104-0012	C-AL	470UF,20%,25V,GP,10X16MM,J	
C408	2201-000556	31417-106-090	C-CERAMIC,DISC	470PF,10%,500V,Y5P,6X3.5M	
C409	31607-402-320		C-ELECTROLYTIC	CE04M TAPG 50V 470M-M(RO)	
C410	A1104-0741		C-ELEC	CE 04 -401105 250V T 2R2-	
C411	2201-000556	31417-106-090	C-CERAMIC,DISC	470PF,10%,500V,Y5P,6X3.5M	
C412	2401-000927	31607-403-500	C-AL	22UF,20%,250V,GP,13X20MM,J	
C413	2301-000224	31507-127-008	C-FILM,PEF	22NF,5%,50V,7.4X3.9X13MM,J	
△ C414	2306-000122	B1102-0318	C-FILM,MPPF	100NF,5%,50V,7.3X4.0X5.0M	
△ C415	2401-000832	31607-401-690	C-AL	220UF,20%,25V,GP,8X11MM,5	
△ C416	2401-000839	A1104-0527	C-AL	220UF,20%,25V,WT,10X12.5M	
C417	2201-000599	31417-468-561	C-CERAMIC,DISC	560PF,10%,500V,Y5P,6X4MM,	
△ C418	2306-000122	B1102-0318	C-FILM,MPPF	100NF,5%,50V,7.3X4.0X5.0M	
C501	2305-000289	A1102-0291	C-FILM,MPEF	220NF,5%,63V,-,5MM,TP	
C502	2401-000636	31607-403-580	C-AL	2.2UF,20%,315V,GP,10X12.5	
C503	2202-000243	A1100-0341	C-CERAMIC,MLC-AXIAL	33PF,5%,50V,SL,3.5X19MM,-	
C504	2202-000205	A1100-0812	C-CERAMIC,MLC-AXIAL	22PF,5%,50V,SL,3.5X19MM,-	
C505	2202-002003		C-CERAMIC,MLC-AXIAL	39PF,5%,50V,SL,1.9X3.5MM,J	
C506	A1100-0783		C-CERAMIC	CK 45 F 3KV 103-Z CK45FZ3	
C507	31517-390-502		C-M,POLYESTER	CFS922M TAPG 250V 104-J	
C508	2401-000636	31607-403-580	C-AL	2.2UF,20%,315V,GP,10X12.5	
C601	2202-000279	A1100-0796	C-CERAMIC,MLC-AXIAL	47PF,5%,50V,SL,3.5X19MM,-	
C602	2202-000279	A1100-0796	C-CERAMIC,MLC-AXIAL	47PF,5%,50V,SL,3.5X19MM,-	
C603	2306-000122	B1102-0318	C-FILM,MPPF	100NF,5%,50V,7.3X4.0X5.0M	
C604	2301-000201	31507-127-002	C-FILM,PEF	2.2NF,5%,50V,7.4X3.9X13MM	
C605	2301-000224	31507-127-008	C-FILM,PEF	22NF,5%,50V,7.4X3.9X13MM,J	
C606	2301-000224	31507-127-008	C-FILM,PEF	22NF,5%,50V,7.4X3.9X13MM,	
C607	2301-000192	31507-127-000	C-FILM,PEF	1NF,5%,50V,5.3X10MM,5MM,T	
C608	2301-000301	31507-127-017	C-FILM,PEF	6.8NF,5%,50V,6.5X5.5X3.0X	
C609	2306-000122	B1102-0318	C-FILM,MPPF	100NF,5%,50V,7.3X4.0X5.0M	
C610	2301-000301	31507-127-017	C-FILM,PEF	6.8NF,5%,50V,6.5X5.5X3.0X	
C611	2306-000122	B1102-0318	C-FILM,MPPF	100NF,5%,50V,7.3X4.0X5.0M	
C612	2305-000289	A1102-0291	C-FILM,MPEF	220NF,5%,63V,-,5MM,TP	
C613	2305-000289	A1102-0291	C-FILM,MPEF	220NF,5%,63V,-,5MM,TP	
C614	2401-001397	A1104-0012	C-AL	470UF,20%,25V,GP,10X16MM,	
C615	2301-000320	31507-127-021	C-FILM,PEF	82NF,5%,50V,8.0X4.5X8.5MM	
C616	2201-000642	31417-104-270	C-CERAMIC,DISC	680PF,10%,50V,Y5P,4.0X4.0	
C617	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C618	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C619	2401-000947	31607-402-070	C-AL	22UF,20%,35V,GP,5X11MM,-J	
C620	2401-000947	31607-402-070	C-AL	22UF,20%,35V,GP,5X11MM,-J	
C621	2201-000471	31417-104-330	C-CERAMIC,DISC	330PF,10%,50V,Y5P,4X3.5MM	
C622	2201-000471	31417-104-330	C-CERAMIC,DISC	330PF,10%,50V,Y5P,4X3.5MM	
C623	2401-001026	31607-402-230	C-AL	3.3UF,20%,50V,GP,5X11MM,5	
C624	2401-001026	31607-402-230	C-AL	3.3UF,20%,50V,GP,5X11MM,5	
C625	2301-000264	31507-127-016	C-FILM,PEF	4.7NF,5%,50V,6.5X5.5X3.0X	
C626	2301-000264	31507-127-016	C-FILM,PEF	4.7NF,5%,50V,6.5X5.5X3.0X	
C627	A1104-0472		C-ELEC	CE 04 -40/85 25V T 102-M	
C628	2306-000122	B1102-0318	C-FILM,MPPF	100NF,5%,50V,7.3X4.0X5.0M	
C631	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C632	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
C633	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	

Loc No	New Code No	Old Code No	Description	Specification	Remarks
C634	31607-402-200		C-ELECTROLYTIC	CE04W TAPG 50V 0.47M	
C635	2401-000480	31607-402-250	C-AL	10UF, 20%, 50V, GP, 5X11MM, 5M	
C636	2401-000480	31607-402-250	C-AL	10UF, 20%, 50V, GP, 5X11MM, 5M	
C637	2301-000192	31507-127-000	C-FILM, PEF	1NF, 5%, 50V, 5.3X10MM, 5MM, T	
C651	2301-000380	31507-127-006	C-FILM, PEF	10NF, 5%, 50V, 6.5X3MM, 5MM, T	
C701	2401-000269	31607-401-470	C-AL	100UF, 20%, 16V, GP, 6X11MM, 5	
C702	2401-000480	31607-402-250	C-AL	10UF, 20%, 50V, GP, 5X11MM, 5M	
C703	2401-000480	31607-402-250	C-AL	10UF, 20%, 50V, GP, 5X11MM, 5M	
C704	2401-000480	31607-402-250	C-AL	10UF, 20%, 50V, GP, 5X11MM, 5M	
C705	2401-000480	31607-402-250	C-AL	10UF, 20%, 50V, GP, 5X11MM, 5M	
C706	2401-000480	31607-402-250	C-AL	10UF, 20%, 50V, GP, 5X11MM, 5M	
C707	2401-000480	31607-402-250	C-AL	10UF, 20%, 50V, GP, 5X11MM, 5M	
C708	A1100-0990		C-CERAMIC	CK104 X7R 16V T 222-M EPO	
C709	A1100-0990		C-CERAMIC	CK104 X7R 16V T 222-M EPO	
C710	2401-000480	31607-402-250	C-AL	10UF, 20%, 50V, GP, 5X11MM, 5M	
C711	2306-000122	81102-0318	C-FILM, MPPF	100NF, 5%, 50V, 7.3X4.0X5.0M	
C712	31607-401-500		C-ELECTROLYTIC	CE04W TAPG 16V 470M-M(SG)	
C713	2202-000127	A1100-0803	C-CERAMIC, MLC-AXIAL	10NF, +80-20%, 25V, Y5V, -, 7	
△ C801	2401-001386	31609-979-001	C-AL	470UF, 20%, 250V, GP, 22X50MM	
△ C802	31467-102-010		C-CERAMIC, AC	CK45P TAPG E250V 222-M(T2	
△ C803	31467-102-010		C-CERAMIC, AC	CK45P TAPG E250V 222-M(T2	
△ C804	31466-504-060		C-CERAMIC, AC	ECK-ZNS 472MEX(R0)	
C805	31417-901-400		C-CERAMIC, HIQ	CK45(T) B2KM 561-K	
C806	31609-403-360		C-ELECTROLYTIC	CE04W 200V 220U-HA(22X35)	
C807	2201-000599	31417-468-561	C-CERAMIC, DISC	560PF, 10%, 500V, Y5P, 6X4MM,	
C808	A1104-0740		C-ELEC	CE 04 -551105 25V T 471-M	
△ C809	2401-000318	A1104-0559	C-AL	100UF, 20%, 25V, WT, 8X11.5MM	
△ C810	2306-000122	81102-0318	C-FILM, MPPF	100NF, 5%, 50V, 7.3X4.0X5.0M	
△ C811	2401-000287	A1104-0368	C-AL	100UF, 20%, 16V, WT, 6X11MM, 5	
△ C812	2401-000287	A1104-0368	C-AL	100UF, 20%, 16V, WT, 6X11MM, 5	
C813	2401-001495	31607-401-460	C-AL	47UF, 20%, 16V, GP, 5X11MM, 5M	
△ C814	2306-000159	A1102-0316	C-FILM, MPPF	220NF, 20%, 250V, -, 22.5MM, B	
C815	31607-403-990		C-ELECTROCYTIC	CE04W TAPG 200V 100M-M(16	
C816	2401-002211	A1104-0810	C-AL	1000UF, 20%, 35V, -, 13X25.5M	
△ C817	2303-000159	31509-391-090	C-FILM, PPF	2.2NF, 5%, 1.6KV, 28X13.5X8,	
C818	2401-000493	A1104-0571	C-AL	10UF, 20%, 50V, WT, 5X11MM, 5M	
C819	2201-000599	31417-468-561	C-CERAMIC, DISC	560PF, 10%, 500V, Y5P, 6X4MM,	
C820	A1104-0472		C-ELEC	CE 04 -40/85 25V T 102-M	
△ C822	2306-000159	A1102-0316	C-FILM, MPPF	220NF, 20%, 250V, -, 22.5MM, B	
C851	A1104-0770		C-ELEC	CE 04 -40/+105 35V T 471-	
C852	31607-402-110		C-ELECTROCYTIC	CE04W TAPG 35V 22CM-M	
C853	2401-000395	31607-403-210	C-AL	10UF, 20%, 160V, GP, 10X12.5M	
△ C854	2305-000407	A1102-0324	C-FILM, MPEF	470NF, 5%, 100V, -, 5MM, TP	
C855	31417-901-400		C-CERAMIC, HIQ	CK45(T) B2KM 561-K	
△ C856	2401-000901	31607-403-220	C-AL	22UF, 20%, 160V, GP, 10X20MM,	
C862	31607-402-240		C-ELECTROCYTIC	CE04W TAPG 50V 4.7M	
C902	2202-000173	A1100-0338	C-CERAMIC, MLC-AXIAL	1NF, 10%, 50V, Y5P, 1.9X3.5MM	
C903	2401-001495	31607-401-460	C-AL	47UF, 20%, 16V, GP, 5X11MM, 5M	
C904	2202-000173	A1100-0338	C-CERAMIC, MLC-AXIAL	1NF, 10%, 50V, Y5P, 1.9X3.5MM	
C905	31607-402-200		C-ELECTROLYTIC	CE04W TAPG 50V 0.47M	
C906	2201-000471	31417-104-330	C-CERAMIC, DISC	330PF, 10%, 50V, Y5P, 4X3.5MM	
C907	2401-001495	31607-401-460	C-AL	47UF, 20%, 16V, GP, 5X11MM, 5M	
C908	2201-000600	31417-104-560	C-CERAMIC, DISC	560PF, 10%, 50V, Y5P, 4X3.5MM	
C909	2201-000651	31407-105-300	C-CERAMIC, DISC	68PF, 5%, 50V, NPO, 8X3, 5, TP	
C910	2401-000480	31607-402-250	C-AL	10UF, 20%, 50V, GP, 5X11MM, 5M	
C911	2401-000480	31607-402-250	C-AL	10UF, 20%, 50V, GP, 5X11MM, 5M	
C913	2202-000127	A1100-0803	C-CERAMIC, MLC-AXIAL	10NF, +80-20%, 25V, Y5V, -, 7	
C914	2202-000173	A1100-0338	C-CERAMIC, MLC-AXIAL	1NF, 10%, 50V, Y5P, 1.9X3.5MM	
C915	2306-000122	B1102-0316	C-FILM, MPPF	100NF, 5%, 50V, 7.3X4.0X5.0M	
C916	2201-000119	31417-344-104	C-CERAMIC, DISC	100NF, +80-20%, 50V, Y5V, 8X5	
C920	2301-000125	31507-121-920	C-FILM, PEF	100NF, 20%, 100V, 14.5X5.7X8	
C933	2401-000832	31607-401-690	C-AL	220UF, 20%, 25V, GP, 8X11MM, 5	

Loc No	New Code No	Old Code No	Description	Specification	Remarks
C957	2401-000832	31607-401-690	C-AL	220UF,20%,25V,GP,8X11MM,5	
C966	2202-000173	A1100-0338	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,1.9X3.5MM	
CK01	2202-000127	A1100-0803	C-CERAMIC,MLC-AXIAL	10NF,+80-20%,25V,Y5V,-,7J	
CK02	2202-000127	A1100-0803	C-CERAMIC,MLC-AXIAL	10NF,+80-20%,25V,Y5V,-,7J	
CK03	31607-402-200		C-ELECTROLYTIC	CE04W TAPG 50V 0.47M	
CK04	31607-402-200		C-ELECTROLYTIC	CE04W TAPG 50V 0.47M	
CK05	2401-001495	31607-401-460	C-AL	47UF,20%,16V,GP,5X11MM,5M	
CK06	2202-000286	A1100-0879	C-CERAMIC,MLC-AXIAL	56PF,5%,50V,SL,1.9X3.5MM	
CLMP/W	AA65-30003A	33333-0011-000	CLAMP-WIRE	-,NYLON-66,V0,NTR,V-MODEL	
CN501	AA39-20070A	36434-0010-000	LEAD-CONNECTOR,ASSY	-,YBNH025-07,67096-007,7P	
CN502	33347-108-110		POST-HEADER	67094-007 (AUTO)	
CN601L	33347-108-310		POST-HEADER	67094-003(AUTO)	
CN601R	33347-114-810		POST-HEADER	YK025-04(AUTO)	
CN602	33347-108-140		POST-HEADER	67094-006 (AUTO)	
CN902	33347-110-150		POST-HEADER	67094-008 (AUTO)	
CN002	33347-108-310		POST-HEADER	67094-003(AUTO)	
CJ02	2306-000122	81102-0318	C-FILM,MPPF	100NF,5%,50V,7.3X4.0X5.0M	
CW01	A1104-0472		C-ELEC	CE 04 -40185 25V T 102-M	
CW02	2306-000122	B1102-0318	C-FILM,MPPF	100NF,5%,50V,7.3X4.0X5.0M	
CW03	2401-000603	31607-402-210	C-AL	1UF,20%,50V,GP,5X11MM,5MM	
CW04	2301-000224	31507-127-008	C-FILM,PEF	22NF,5%,50V,7.4X3.9X13MM,]	
CW05	2301-000160	A1102-0234	C-FILM,PEF	12NF,5%,50V,11.0X6.0X9.0M	
CW06	31607-402-720		C-ELECTROLYTIC	CE04W TAPG 50V 2.2M-M(NP)	
CW07	A1104-0472		C-ELEC	CE 04 -40185 25V T 102-M	
CW08	2306-000122	81102-0318	C-FILM,MPPF	100NF,5%,50V,7.3X4.0X5.0M	
CW09	31607-402-260		C-ELECTROLYTIC	CE04W TAPG 50V 22M-M	
CW10	2401-001625	31607-402-550	C-AL	6.8UF,20%,50V,GP,5X11MM,5	
CW11	2305-000289	A1102-0291	C-FILM,MPEF	220NF,5%,63V,-,5MM,TP	
CW12	2305-000289	A1102-0291	C-FILM,MPEF	220NF,5%,63V,-,5MM,TP	
CW13	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
CW14	31607-402-200		C-ELECTROLYTIC	CE04W TAPG 50V 0.47M	
CX01	2202-000127	A1100-0803	C-CERAMIC,MLC-AXIAL	10NF,+80-20%,25V,Y5V,-,7J	
CX02	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
CX03	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
CX04	2201-000556	31417-106-090	C-CERAMIC,DISC	470PF,10%,500V,Y5P,6X3.5M	
0201	0402-000129	32167-201-070	DIODE-RECTIFIER	1N4003,200V,1A,DO-41	
0231	32167-406-480		DIODE	1N4148 TAPG	
0232	32167-406-480		DIODE	1N4148 TAPG	
0233	32167-406-480		DIODE	1N4148 TAPG	
0261	32167-406-480		DIODE	1N4148 TAPG	
0262	32167-406-480		DIODE	1N4148 TAPG	
0301	0402-000546	32167-201-170	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41	
D402	0402-000129	32167-201-070	DIODE-RECTIFIER	1N4003,200V,1A,DO-41	
⚠ D403	0402-000493	32167-207-120	DIODE-RECTIFIER	1R5GU41,400V,1.5A,DO-15L	
D404	0402-000546	32167-201-170	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41	
0405	0402-000546	32167-201-170	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41	
⚠ 0501	0402-000133	B4104-0002	DIODE-RECTIFIER	1N4004GP,400V,1A,DO-41	
0601	32167-406-480		DIODE	1N4148 TAPG	
⚠ D801	B4104-0112		DIODE-RECTIFIER	RBV606LFB 600V 6A ST BRID	
D802	0402-000546	32167-201-170	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41	
⚠ 0803	0402-000493	32167-207-120	DIODE-RECTIFIER	1R5GU41,400V,1.5A,DO-15L	
⚠ D804	0402-000213	32167-208-580	DIODE-RECTIFIER	ERB12-06,600V,1.0A,DO-41	
0805	0402-000546	32167-201-170	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41	
D806	0402-000546	32167-201-170	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41	
⚠ 0807	0402-000493	32167-207-120	DIODE-RECTIFIER	1R5GU41,400V,1.5A,DO-15L	
D808	0402-000129	32167-201-070	DIODE-RECTIFIER	1N4003,200V,1A,DO-41	
⚠ 0811	0402-000540	84102-0068	DIODE-RECTIFIER	RU20A,600V,1.5A,-	
0812	32167-406-480		DIODE	1N4148 TAPG	
0813	0402-000546	32167-201-170	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41	
0814	0402-000546	32167-201-170	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41	
D903	32167-406-480		DIODE	1N4148 TAPG	
0905	32167-406-480		DIODE	1N4148 TAPG	




Loc No	New Code No	Old Code No	Description	Specification	Remarks
D951	0402-000129	32167-201-070	DIODE-RECTIFIER	1N4003, 200V, 1A, DO-41	
DW01	32167-406-480		DIODE	1N4148 TAPG	
DW02	32167-406-480		DIODE	1N4148 TAPG	
DX01	32167-408-080		DIODE-ZENER	EQA02-06D/MTZ6.2B(TAPG)	
DX02	0402-000546	32167-201-170	DIODE-RECTIFIER	TVR10G, 400V, 1.0A, DO-41	
DZ101	0403-000700	A4106-0227	DIODE-ZENER	TZP33A, 33V, 31-35V, 1W, DO-4	
DZ201	0403-000663	A4106-0229	DIODE-ZENER	MTZ3.3B, 3.3V, 3.32-3.53V, 5	
02223	32167-401-800		DIODE-ZENER	EQA02-06A/MTZ5.6B(TAPG)	
DZ601	0403-000654	32167-406-250	DIODE-ZENER	MTZ12, 12V, 11.4-12.6V, 500M	
DZ602	0403-000654	32167-406-250	DIODE-ZENER	MTZ12, 12V, 11.4-12.6V, 500M	
02603	0403-000654	32167-406-250	DIODE-ZENER	MTZ12, 12V, 11.4-12.6V, 500M	
DZ604	0403-000654	32167-406-250	DIODE-ZENER	MTZ12, 12V, 11.4-12.6V, 500M	
02605	0403-000654	32167-406-250	DIODE-ZENER	MTZ12, 12V, 11.4-12.6V, 500M	
DZ606	0403-000654	32167-406-250	DIODE-ZENER	MTZ12, 12V, 11.4-12.6V, 500M	
DZ607	0403-000656	32167-403-780	DIODE-ZENER	MTZ15C, 15V, 14.35-15.09V, 5	
DZ701	0403-000654	32167-406-250	DIODE-ZENER	MTZ12, 12V, 11.4-12.6V, 500M	
DZ702	0403-000654	32167-406-250	DIODE-ZENER	MTZ12, 12V, 11.4-12.6V, 500M	
DZ703	0403-000654	32167-406-250	DIODE-ZENER	MTZ12, 12V, 11.4-12.6V, 500M	
△ DZ801	1405-000188	32167-401-041	VARIATOR	430V, 1250A, 14X7.5MM, TP	
△ DZ802	1405-000188	32167-401-041	VARIATOR	430V, 1250A, 14X7.5MM, TP	
△ 02803	0403-000697	A4106-0237	DIODE-ZENER	TZP10A, 10V, 9.4-10.6V, 1W, D	
02804	32167-406-080		DIODE-ZENER	MTZ 5.18	
DZ901	32167-401-800		DIODE-ZENER	EQA02-06A/MTZ5.6B(TAPG)	
DZ902	32167-401-800		DIODE-ZENER	EQA02-06A/MTZ5.6B(TAPG)	
DZ903	32167-401-800		DIODE-ZENER	EQA02-06A/MTZ5.6B(TAPG)	
DZ904	32167-401-800		DIODE-ZENER	EQA02-06A/MTZ5.6B(TAPG)	
DZ905	32167-401-800		DIODE-ZENER	EQA02-06A/MTZ5.6B(TAPG)	
DZ906	32167-401-800		DIODE-ZENER	EQA02-06A/MTZ5.6B(TAPG)	
DZ907	32167-401-800		DIODE-ZENER	EQA02-06A/MTZ5.6B(TAPG)	
DZ908	32167-401-800		DIODE-ZENER	EQA02-06A/MTZ5.6B(TAPG)	
EYELET	AA60-40011A	33104-107-210	EYELET	-, ID2.0, OD2.8, -, -, BST	EY100-EY843
EYELET	AA60-40011B	33104-107-220	EYELET	-, ID2.2, OD3.2, -, -, BSP	EL101-EL810
△ F801	3601-000144	34709-087-170	FUSE-FERRULE	125V, 4A, SLOW BLOW, GLASS, 5	
F801A	3602-000114	33167-001-001	FUSE-HOLDER	-, -, 30MOHM	
F801B	3602-000114	33167-001-001	FUSE-HOLDER	-, -, 30MOHM	
GT-PIN	AA60-40014A	33124-111-100	PIN-GT, ASSY	1P, -, -, AUTO	PIN-GT, ALL
GT101	AA39-20010C	33054-834-017	LEAD-CONNECTOR, ASSY	-, YFH800-01, S, 1P, 600, 1617	
△ H001	AA59-40002F	37179-0006-000	MODULE-RF S/W	-, 2GR-10UT, NTSC, USA, -, -	
△ HC801	AA13-20002Q	A4010-0082	IC-HYBRID	-, FL001, SIP, 6P, FEEDBACK	
△ HC802	AA13-20002R	A4010-0083	IC-HYBRID	-, PCL001, SIP, 6P, POWER CON	
△ IC201	B4012-0400		IC-LINEAR	TA1201AN SDIP, 56PIN NTCH	
△ IC451	1203-000298	A4008-0520	IC-POSITIVE FIXED REG.	7809, TO-220, 3P, -, PLASTIC,	
△ IC602	B4012-0286		IC-LINEAR	UPC1853CT DIP TV-VIDEO(VR)	
△ IC604	AA59-40002D	32199-411-090	MODULE-MTS	-, SBX1637A, ZENITH, USA, -, -	
IC701	32119-101-730		ICI	M51321P	
△ IC851	0604-000117	32309-024-040	PHOTO-COUPLER	TR, 130-260%, 200MW, DIP-4, S	
△ IC852	AA13-20002L	B4010-0067	IC-HYBRID	-, SE125N, SIP, 3P, ERROR AMP	
△ IC901	AA13-30006K	B4002-0893	IC-MCU	-, Z8933212PSC-R2497, 16811	
△ IC902	1103-000189	64000-0049	IC-EEPROM	24C02, 256+8BIT, DIP, 8P, 300	
△ ICX01	B4012-0360		IC-LINEAR	LA7510 SIP 9P	
ICW01	32119-201-010		ICI	MC 4558C	
J213	2701-000115	32427-805-840	INDUCTOR-AXIAL	10UH, 10%, 2.8X7MM	
JA701	3722-000499	A3040-0198	JACK-RCA	9P(S), -, -, SN	
L-CAUT	AA68-50064E	38114-700-210	LABEL-INDICATOR	A/P120(S), TO.2, -, -, WHT, UL	
L-SET	AA68-50088A	38114-708-210	LABEL-SET	A/P120(S), -, -, -, -, USA A	
L101	2701-000114	32427-904-924	INDUCTOR-AXIAL	10UH, 10%, 2.5X3.4MM	
L111	3301-000287	34047-019-060	CORE-FERRITE BEAD	AA, 3.5X1.0X6.0MM, 1500, 240	
L152	2701-000304	32427-904-945	INDUCTOR-AXIAL	0.8UH, 10%, 2.5X3.4MM	
L201	AA26-10004K	A1193-0008	TRANS-IF	-, 7MG, SIF, -, 7MM, 100PF, 4.5	
L203	2701-000127	32427-904-926	INDUCTOR-AXIAL	15UH, 10%, 2.5X3.4MM	
L204	2701-000207	A1132-0060	INDUCTOR-AXIAL	56UH, 5%, 2.5X3.4MM	
L205	AA26-10004C	A1190-0010	TRANS-IF	-, 7MG, VIF, 0.37UH, 7MM, 27PF	

Loc No	New Code No	Old Code No	Description	Specification	Remarks
L206	2701-000113	A1132-0056	INDUCTOR-AXIAL	100UH, 5%, 2.5X3.4MM	
L208	2701-000114	32427-904-924	INDUCTOR-AXIAL	10UH, 10%, 2.5X3.4MM	
L301	2701-000116	32427-805-882	INDUCTOR-AXIAL	10UH, 10%, 4.2X9.8MM	
△ L401	AA27-30001B	32446-705-050	COIL-LINEARITY	-, 195UH, Q1C1010, P10.4, 4.5	
△ L403	AA27-10001D	32426-833-020	COIL-CHOKE	-, 6.8MH, K, 50, 150MA, ST, 6.8	
L404	3301-000287	34047-019-060	CORE-FERRITE BEAD	AA, 3.5X1.0X6.0MM, 1500, 240	
L405	3301-000287	34047-019-060	CORE-FERRITE BEAD	AA, 3.5X1.0X6.0MM, 1500, 240	
L450	AA27-10002Y	B1133-0009	COIL-CHOKE	-, 100UH, K, 10, 700MA, T, 100U	
L601	2701-000180	A1132-0089	INDUCTOR-AXIAL	33UH, 5%, 2.5X3.4MM	
L701	2701-000207	A1132-0060	INDUCTOR-AXIAL	56UH, 5%, 2.5X3.4MM	
△ L801	AA29-30001D	32426-633-160	FILTER-LINE	-, 6.0MH, 2A, -, SQ1913	
△ L802	AA27-20002T	32479-027-710	COIL-DEGAUSSING	-, 14", 40HM, 30T, L940, D	
△ L803	AA29-30001D	32426-633-160	FILTER-LINE	-, 6.0MH, 2A, -, SQ1913	
L804	A1247-0054		FILTER-EMI BEAD	HF70ZBF3.5X5X0.8 SB 30U-M	
L807	3301-000287	34047-019-060	CORE-FERRITE BEAD	AA, 3.5X1.0X6.0MM, 1500, 240	
L809	AA27-10002Y	B1133-0009	COIL-CHOKE	-, 100UH, K, 10, 700MA, T, 100U	
L810	AA27-10002Y	B1133-0009	COIL-CHOKE	-, 100UH, K, 10, 700MA, T, 100U	
L811	A1247-0054		FILTER-EMI BEAD	HF70ZBF3.5X5X0.8 SB 30CHM	
L812	A1247-0054		FILTER-EMI BEAD	HF70ZBF3.5X5X0.8 SB 30CHM	
L863	3301-000287	34047-019-060	CORE-FERRITE BEAD	AA, 3.5X1.0X6.0MM, 1500, 240	
L864	3301-000287	34047-019-060	CORE-FERRITE BEAD	AA, 3.5X1.0X6.0MM, 1500, 240	
L901	2701-000114	32427-904-924	INDUCTOR-AXIAL	10UH, 10%, 2.5X3.4MM	
L902	2701-000114	32427-904-924	INDUCTOR-AXIAL	10UH, 10%, 2.5X3.4MM	
L904	A1247-0054		FILTER-EMI BEAD	HF70ZBF3.5X5X0.8 SB 30CHM	
LK01	2701-000114	32427-904-924	INDUCTOR-AXIAL	10UH, 10%, 2.5X3.4MM	
△ NT801	A1334-0019		THERMISTOR	KL11L4R7-3.5A 4.7OHM/25DE	
△ P801	81332-0018		POSISTOR	PTH631D02BF7ROM140TI DEGAU	
P0801	AA39-10002X	A6006-0253	POWER-CORD	-, KJ-10, SPT2, 2.4M, HOUS, UL	
0151	0501-000384	32137-301-090	TR-SMALL SIGNAL	2SC388ATM, NPN, 30V, 25V, 50M	
0202	32137-301-720		TRANSISTOR	KSC 815-Y(TAPG)/YTAM	
0203	32137-301-720		TRANSISTOR	KSC 815-Y(TAPG)/YTAM	
0251	32137-301-720		TRANSISTOR	KSC 815-Y(TAPG)/YTAM	
△ Q402	32137-301-560		TRANSISTOR	KSC 2331-Y(TAPG)	
Q601	32137-301-720		TRANSISTOR	KSC 815-Y(TAPG)/YTAM	
Q621	32137-301-720		TRANSISTOR	KSC 815-Y(TAPG)/YTAM	
Q701	0504-000123	A4060-0033	TR-DIGITAL	KSR1010, NPN, 300MW, 10K, TO-	
Q702	0504-000123	A4060-0033	TR-DIGITAL	KSR1010, NPN, 300MW, 10K, TO-	
△ Q801	A4058-0009		TR-DARLINGTON	TIP102 2W 8A 100V SI/NPN	
△ Q802	0502-000244	A4052-0055	TR-POWER	KSA940, PNP, -150V, -150V, -1	
Q901	32137-301-560		TRANSISTOR	KSC 2331-Y(TAPG)	
Q902	32137-301-720		TRANSISTOR	KSC 815-Y(TAPG)/YTAM	
Q909	0504-000123	A4060-0033	TR-DIGITAL	KSR1010, NPN, 300MW, 10K, TO-	
QW01	32137-301-720		TRANSISTOR	KSC 815-Y(TAPG)/YTAM	
QW02	32137-301-720		TRANSISTOR	KSC 815-Y(TAPG)/YTAM	
QX01	32137-401-530		TRANSISTOR	KSA 539-Y(TAPG)/YTAM	
R101	2001-000429	31018-177-102	R-CARBON	1KOHM, 5%, 1/8W, AA, TP, 1.8X3	
R102	2004-001301	31018-177-823	R-METAL	82KOHM, 5%, 1/8W, AA, TP, 1.8X	
R103	2001-000290	31018-177-103	R-CARBON	10KOHM, 5%, 1/8W, AA, TP, 1.8X	
R106	2001-001146	31018-377-479	R-CARBON(S)	4.7OHM, 5%, 1/2W, AA, TP, 2.4X	
R152	2001-000221	31018-177-122	R-CARBON	1.2KOHM, 5%, 1/8W, AA, TP, 1.8	
R153	2001-000577	31018-177-202	R-CARBON	2KOHM, 5%, 1/8W, AA, TP, 1.8X3	
R154	2001-000780	31018-177-471	R-CARBON	470OHM, 5%, 1/8W, AA, TP, 1.8X	
R155	2004-001240	31018-177-750	R-METAL	75OHM, 5%, 1/8W, AA, TP, 1.8X3	
R156	2001-000281	31018-177-101	R-CARBON	100OHM, 5%, 1/8W, AA, TP, 1.8X	
R157	2001-000793	31018-177-470	R-CARBON	47OHM, 5%, 1/8W, AA, TP, 1.8X3	
R201	2001-000429	31018-177-102	R-CARBON	1KOHM, 5%, 1/8W, AA, TP, 1.8X3	
R202	2001-000734	31018-177-472	R-CARBON	4.7KOHM, 5%, 1/8W, AA, TP, 1.8	
R203	2001-000734	31018-177-472	R-CARBON	4.7KOHM, 5%, 1/8W, AA, TP, 1.8	
R207	2001-001111	A1000-0646	R-CARBON(S)	240OHM, 5%, 1/2W, AA, TP, 2.4X	
R211	2001-000281	31018-177-101	R-CARBON	100OHM, 5%, 1/8W, AA, TP, 1.8X	
R212	2001-000281	31018-177-101	R-CARBON	100OHM, 5%, 1/8W, AA, TP, 1.8X	
R218	2001-000577	31018-177-202	R-CARBON	2KOHM, 5%, 1/8W, AA, TP, 1.8X3	

Loc No	New Code No	Old Code No	Description	Specification	Remarks
A219	2001-000674	31018-177-361	R-CARBON	360OHM,5%,1/8W,AA,TP,1.8X	
R220	2001-000331	31018-177-123	R-CARBON	12KOHM,5%,1/8W,AA,TP,1.8X	
R222	2001-000591	31018-177-332	R-CARBON	3.3KOHM,5%,1/8W,AA,TP,1.8	
R223	2001-000591	31018-177-332	R-CARBON	3.3KOHM,5%,1/8W,AA,TP,1.8	
R224	2001-000591	31018-177-332	R-CARBON	3.3KOHM,5%,1/8W,AA,TP,1.8	
R225	2001-000837	31018-177-513	R-CARBON	51KOHM,5%,1/8W,AA,TP,1.8X	
R226	2001-000290	31018-177-103	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X	
R227	2001-000508	31018-177-224	R-CARBON	220KOHM,5%,1/8W,AA,TP,1.8	
R228	2001-000258	31018-177-182	R-CARBON	1.8KOHM,5%,1/8W,AA,TP,1.8	
R229	2001-000258	31018-177-182	R-CARBON	1.8KOHM,5%,1/8W,AA,TP,1.8	
R230	2001-000591	31018-177-332	R-CARBON	3.3KOHM,5%,1/8W,AA,TP,1.8	
R231	2001-000660	31018-177-333	R-CARBON	33KOHM,5%,1/8W,AA,TP,1.8X	
R233	2004-001234	31018-177-753	R-METAL	75KOHM,5%,1/8W,AA,TP,1.8X	
R234	2004-001193	31018-177-681	R-METAL	680OHM,5%,1/8W,AA,TP,1.8X	
R239	2004-001213	31018-177-752	R-METAL	7.5KOHM,5%,1/8W,AA,TP,1.8	
R240	2001-000577	31018-177-202	R-CARBON	2KOHM,5%,1/8W,AA,TP,1.8X3	
R241	2001-000857	31018-177-561	R-CARBON	560OHM,5%,1/8W,AA,TP,1.8X	
R242	2001-000857	31018-177-561	R-CARBON	560OHM,5%,1/8W,AA,TP,1.8X	
R251	2001-000362	31018-177-151	R-CARBON	150OHM,5%,1/8W,AA,TP,1.8X	
R252	2001-000362	31018-177-151	R-CARBON	150OHM,5%,1/8W,AA,TP,1.8X	
R261	2001-000397	31018-177-184	R-CARBON	180KOHM,5%,1/8W,AA,TP,1.8	
R262	2001-000773	31018-177-474	R-CARBON	470KOHM,5%,1/8W,AA,TP,1.8	
R271	2001-000515	31018-177-221	R-CARBON	220OHM,5%,1/8W,AA,TP,1.8X	
R272	2001-000515	31018-177-221	R-CARBON	220OHM,5%,1/8W,AA,TP,1.8X	
R273	2001-000515	31018-177-221	R-CARBON	220OHM,5%,1/8W,AA,TP,1.8X	
R301	2001-000003	31018-177-331	R-CARBON	330OHM,5%,1/8W,AA,TP,1.8X	
R302	2001-000660	31018-177-333	R-CARBON	33KOHM,5%,1/8W,AA,TP,1.8X	
R303	2004-001104	31018-177-563	R-METAL	56KOHM,5%,1/8W,AA,TP,1.8X	
R304	2003-001036	A1004-0456	R-METAL OXIDE(S)	3.3OHM,5%,2W,AF,TP,3.9X10	
R305	2004-001301	31018-177-823	R-METAL	82KOHM,5%,1/8W,AA,TP,1.8X	
R306	2001-000003	31018-177-331	R-CARBON	330OHM,5%,1/8W,AA,TP,1.8X	
R307	2001-000679	31018-177-363	R-CARBON	36KOHM,5%,1/8W,AA,TP,1.8X	
R308	2001-000633	31018-177-303	R-CARBON	30KOHM,5%,1/8W,AA,TP,1.8X	
R309	2003-000649	A1004-0418	R-METAL OXIDE(S)	330OHM,5%,1W,AD,TP,3.3X9M	
R401	2001-000780	31018-177-471	R-CARBON	470OHM,5%,1/8W,AA,TP,1.8X	
R402	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3	
R403	2001-001114	31018-377-271	R-CARBON(S)	270OHM,5%,1/2W,AA,TP,2.4X	
R404	2001-000020	31018-377-220	R-CARBON(S)	22OHM,5%,1/2W,AA,TP,2.4X6	
△ R405	2003-000540	A1004-0404	R-METAL OXIDE(S)	1KOHM,5%,2W,AD,TP,4X12MM	
△ R406	2008-000262	A1010-0063	R-FUSIBLE(S)	150OHM,5%,2W,AF,TP,3.9X10	
R407	2001-000022	31018-377-330	R-CARBON(S)	33OHM,5%,1/2W,AA,TP,2.4X6	
△ R408	2004-001390	31048-361-001	R-METAL(S)	1KOHM,2%,1/2W,AA,TP,2.4X6	
△ R409	2008-000254	A1010-0085	R-FUSIBLE(S)	0.68OHM,5%,2W,AF,TP,3.9X1	
△ R410	2008-000206	A1010-0035	R-FUSIBLE(S)	1OHM,5%,1/2W,AF,TP,2.5X6	
△ R411	2004-001405	31049-375-793	R-METAL(S)	79KOHM,1%,1/2W,AA,TP,2.4X	
△ R412	2004-001408	31049-375-913	R-METAL(S)	91KOHM,1%,1/2W,AA,TP,2.4X	
△ R413	2001-001037	A1000-0660	R-CARBON(S)	0.39OHM,5%,1/2W,AA,TP,2.4	
△ R414	2004-001405	31049-375-793	R-METAL(S)	79KOHM,1%,1/2W,AA,TP,2.4X	
△ R420	31028-328-102		R-COMPOSITION	RC 1/2T 1K-K/ERG-12GK 102	
△ R440	2003-000746	A1004-0427	R-METAL OXIDE(S)	56OHM,5%,2W,AD,TP,4X12MM	
△ R441	2003-001026	A1004-0477	R-METAL OXIDE(S)	180OHM,5%,2W,AF,TP,3.9X10	
△ R442	2003-001026	A1004-0477	R-METAL OXIDE(S)	180OHM,5%,2W,AF,TP,3.9X10	
△ R451	2008-000252	A1010-0038	R-FUSIBLE(S)	0.47OHM,10%,1/2W,AF,TP,2.4	
△ R453	2003-000713	A1004-0428	R-METAL OXIDE(S)	47OHM,5%,2W,AD,TP,4X12MM	
△ R502	2008-000254	A1010-0085	R-FUSIBLE(S)	0.68OHM,5%,2W,AF,TP,3.9X1	
△ R503	31028-328-472		R-COMPOSITION	RC 1/2T 4.7K-K/ERC-12GL 4	
R504	2001-001194	31018-377-823	R-CARBON(S)	82KOHM,5%,1/2W,AA,TP,2.4X	
R505	2001-001194	31018-377-823	R-CARBON(S)	82KOHM,5%,1/2W,AA,TP,2.4X	
R506	2001-001194	31018-377-823	R-CARBON(S)	82KOHM,5%,1/2W,AA,TP,2.4X	
△ R507	2001-001049	A1000-0636	R-CARBON(S)	1.3KOHM,5%,1/2W,AB,TP,2.4	
R508	2001-001106	31018-377-224	R-CARBON(S)	220KOHM,5%,1/2W,AA,TP,2.4	
R509	2001-000780	31018-177-471	R-CARBON	470OHM,5%,1/8W,AA,TP,1.8X	

Loc No	New Code No	Old Code No	Description	Specification	Remarks
R510	2001-000780	31018-177-471	R-CARBON	4700ΩM, 5%, 1/8W, AA, TP, 1.8X	
R511	2001-000780	31018-177-471	R-CARBON	4700ΩM, 5%, 1/8W, AA, TP, 1.8X	
A512	2001-000258	31018-177-182	R-CARBON	1.8KΩM, 5%, 1/8W, AA, TP, 1.8	
R513	2001-000258	31018-177-182	R-CARBON	1.8KΩM, 5%, 1/8W, AA, TP, 1.8	
R514	2001-000258	31018-177-182	R-CARBON	1.8KΩM, 5%, 1/8W, AA, TP, 1.8	
A515	2008-000266	A1010-0061	R-FUSIBLE(S)	10ΩM, 5%, 2W, AF, TP, 3.9X10MM	
R516	2001-001062	31018-377-106	R-CARBON(S)	10MΩM, 5%, 1/2W, AA, TP, 2.4X	
A518	2008-000277	31057-002-040	R-FUSIBLE	680ΩM, 5%, 1/2W, AA, TP, 4.7X1	
R601	2001-000793	31018-177-470	R-CARBON	470ΩM, 5%, 1/8W, AA, TP, 1.8X3	
R602	2001-000577	31018-177-202	R-CARBON	2KΩM, 5%, 1/8W, AA, TP, 1.8X3	
R603	2001-000577	31018-177-202	R-CARBON	2KΩM, 5%, 1/8W, AA, TP, 1.8X3	
R606	2004-001284	31018-177-824	R-METAL	820KΩM, 5%, 1/8W, AA, TP, 1.8	
R607	2001-000281	31018-177-101	R-CARBON	100ΩM, 5%, 1/8W, AA, TP, 1.8X	
R608	2001-000281	31018-177-101	R-CARBON	100ΩM, 5%, 1/8W, AA, TP, 1.8X	
R609	2001-000613	31018-177-392	R-CARBON	3.9KΩM, 5%, 1/8W, AA, TP, 1.8	
R610	2001-000734	31018-177-472	R-CARBON	4.7KΩM, 5%, 1/8W, AA, TP, 1.8	
R611	2001-000009	31018-177-203	R-CARBON	20KΩM, 5%, 1/8W, AA, TP, 1.8X	
R612	2001-000522	31018-177-223	R-CARBON	22KΩM, 5%, 1/8W, AA, TP, 1.8X	
R613	2001-000007	31018-177-302	R-CARBON	3KΩM, 5%, 1/8W, AA, TP, 1.8X3	
R614	2001-000007	31018-177-302	R-CARBON	3KΩM, 5%, 1/8W, AA, TP, 1.8X3	
R615	2001-000429	31018-177-102	R-CARBON	1KΩM, 5%, 1/8W, AA, TP, 1.8X3	
R616	2001-000273	31018-177-104	R-CARBON	100KΩM, 5%, 1/8W, AA, TP, 1.8	
R617	2001-000429	31018-177-102	R-CARBON	1KΩM, 5%, 1/8W, AA, TP, 1.8X3	
R618	2001-001146	31018-377-479	R-CARBON(S)	4.7ΩM, 5%, 1/2W, AA, TP, 2.4X	
R619	2001-000362	31018-177-151	R-CARBON	150ΩM, 5%, 1/8W, AA, TP, 1.8X	
R620	2001-000290	31018-177-103	R-CARBON	10KΩM, 5%, 1/8W, AA, TP, 1.8X	
R621	2004-001258	31018-177-822	R-METAL	8.2KΩM, 5%, 1/8W, AA, TP, 1.8	
R625	2001-000290	31018-177-103	R-CARBON	10KΩM, 5%, 1/8W, AA, TP, 1.8X	
R626	2001-000633	31018-177-303	R-CARBON	30KΩM, 5%, 1/8W, AA, TP, 1.8X	
R627	2001-001146	31018-377-479	R-CARBON(S)	4.7ΩM, 5%, 1/2W, AA, TP, 2.4X	
R633	2004-001258	31018-177-822	R-METAL	8.2KΩM, 5%, 1/8W, AA, TP, 1.8	
R644	2004-001258	31018-177-822	R-METAL	8.2KΩM, 5%, 1/8W, AA, TP, 1.8	
R651	2001-000522	31018-177-223	R-CARBON	22KΩM, 5%, 1/8W, AA, TP, 1.8X	
R652	2001-000522	31018-177-223	R-CARBON	22KΩM, 5%, 1/8W, AA, TP, 1.8X	
R653	2001-000522	31018-177-223	R-CARBON	22KΩM, 5%, 1/8W, AA, TP, 1.8X	
R667	2001-000290	31018-177-103	R-CARBON	10KΩM, 5%, 1/8W, AA, TP, 1.8X	
R705	2001-001187	31018-377-750	R-CARBON(S)	750ΩM, 5%, 1/2W, AA, TP, 2.4X6	
R708	2001-001187	31018-377-750	R-CARBON(S)	750ΩM, 5%, 1/2W, AA, TP, 2.4X6	
R709	2001-001187	31018-377-750	R-CARBON(S)	750ΩM, 5%, 1/2W, AA, TP, 2.4X6	
R712	2001-001071	31018-377-123	R-CARBON(S)	12KΩM, 5%, 1/2W, AA, TP, 2.4X	
R713	2001-000085	31018-377-104	R-CARBON(S)	100KΩM, 5%, 1/2W, AA, TP, 2.4	
R714	2001-001071	31018-377-123	R-CARBON(S)	12KΩM, 5%, 1/2W, AA, TP, 2.4X	
R715	2001-000085	31018-377-104	R-CARBON(S)	100KΩM, 5%, 1/2W, AA, TP, 2.4	
R716	2001-001071	31018-377-123	R-CARBON(S)	12KΩM, 5%, 1/2W, AA, TP, 2.4X	
R717	2001-000085	31018-377-104	R-CARBON(S)	100KΩM, 5%, 1/2W, AA, TP, 2.4	
R718	2001-001071	31018-377-123	R-CARBON(S)	12KΩM, 5%, 1/2W, AA, TP, 2.4X	
R719	2001-000085	31018-377-104	R-CARBON(S)	100KΩM, 5%, 1/2W, AA, TP, 2.4	
R720	2001-000085	31018-377-104	R-CARBON(S)	100KΩM, 5%, 1/2W, AA, TP, 2.4	
R721	2001-000085	31018-377-104	R-CARBON(S)	100KΩM, 5%, 1/2W, AA, TP, 2.4	
R722	2001-000252	31018-177-162	R-CARBON	1.6KΩM, 5%, 1/8W, AA, TP, 1.8	
R723	2001-000429	31018-177-102	R-CARBON	1KΩM, 5%, 1/8W, AA, TP, 1.8X3	
A801	2009-000019	A1008-0013	R-METAL F LATE	0.270ΩM, 10%, 5W, CL, TP, 5X14	
A802	2001-001117	A1000-0586	R-CARBON(S)	2KΩM, 5%, 1/2W, AA, TP, 2.4X6	
A803	2001-001117	A1000-0586	R-CARBON(S)	2KΩM, 5%, 1/2W, AA, TP, 2.4X6	
R804	2001-001150	31018-377-474	R-CARBON(S)	470KΩM, 5%, 1/2W, AA, TP, 2.4	
A805	31028-328-475		R-COMPOSITION	RC 1/2W 4.7M-K/ERC-12G 4	
R806	2001-001071	31018-377-123	R-CARBON(S)	12KΩM, 5%, 1/2W, AA, TP, 2.4X	
R807	2001-001071	31018-377-123	R-CARBON(S)	12KΩM, 5%, 1/2W, AA, TP, 2.4X	
R808	2001-001150	31018-377-474	R-CARBON(S)	470KΩM, 5%, 1/2W, AA, TP, 2.4	
A809	2008-000205	A1010-0052	R-FUSIBLE(S)	100ΩM, 5%, 1/2W, AF, TP, 2.5X6	
A810	2003-000458	A1004-0430	R-METAL OXIDE(S)	100ΩM, 5%, 2W, AD, TP, 4X12MM	
A812	2008-000206	A1010-0035	R-FUSIBLE(S)	10ΩM, 5%, 1/2W, AF, TP, 2.5X6	

Loc. No.	New Code No.	Old Code No.	Description	Specification	Remarks
▲ R814	2001-001117	A1000-0586	R-CARBON(S)	2KOHM, 5%, 1/2W, AA, TP, 2.4X6	
▲ R815	A1014-0085		R- CEMENT	RWC 5 I 220-J 22R	
▲ R816	A1004-0431		R- METAL OXIDE	RS 2 RT(S) 103-J 10K	
▲ R817	A1004-0431		R- METAL OXIDE	RS 2 RT(S) 103-J 10K	
▲ R818	A1004-0431		R- METAL OXIDE	RS 2 RT(S) 103-J 10K	
R819	A1000-0785		R-CARBON	RD 1/2 T(S) 430-J 43R	
▲ R833	2008-000251	A1010-0066	R-FUSIBLE(S)	0.270HM, 10%, 2W, AF, TP, 3.9X	
R851	31018-377-272		R-CARBON/METAL FILM	RD 1/2T 2.7K-J	
R852	2001-001051	31018-377-152	R-CARBON(S)	1.5KOHM, 5%, 1/2W, AB, TP, 2.4	
▲ R853	2003-000713	A1004-0428	R- METAL OXIDE(S)	470HM, 5%, 2W, AD, TP, 4X12MM	
R902	2001-000429	31018-177-102	R-CARBON	1KOHM, 5%, 1/8W, AA, TP, 1.8X	
R903	2001-000281	31018-177-101	R-CARBON	100OHM, 5%, 1/8W, AA, TP, 1.8X	
R904	2001-000281	31018-177-101	R-CARBON	100OHM, 5%, 1/8W, AA, TP, 1.8X	
R906	2001-000472	31018-177-272	R-CARBON	2.7KOHM, 5%, 1/8W, AA, TP, 1.8	
R910	2001-000252	31018-177-162	R-CARBON	1.6KOHM, 5%, 1/8W, AA, TP, 1.8	
R911	2001-000290	31018-177-103	R-CARBON	10KOHM, 5%, 1/8W, AA, TP, 1.8X	
A912	2001-000449	31018-177-222	R-CARBON	2.2KOHM, 5%, 1/8W, AA, TP, 1.8	
R913	2001-000449	31018-177-222	R-CARBON	2.2KOHM, 5%, 1/8W, AA, TP, 1.8	
R918	2004-001258	31018-177-822	R- METAL	8.2KOHM, 5%, 1/8W, AA, TP, 1.8	
R920	2001-000290	31018-177-103	R-CARBON	10KOHM, 5%, 1/8W, AA, TP, 1.8X	
R922	2001-000281	31018-177-101	R-CARBON	100OHM, 5%, 1/8W, AA, TP, 1.8X	
R923	2001-000281	31018-177-101	R-CARBON	100OHM, 5%, 1/8W, AA, TP, 1.8X	
R924	2001-000449	31018-177-222	R-CARBON	2.2KOHM, 5%, 1/8W, AA, TP, 1.8	
R925	2001-000449	31018-177-222	R-CARBON	2.2KOHM, 5%, 1/8W, AA, TP, 1.8	
R927	2001-000290	31018-177-103	R-CARBON	10KOHM, 5%, 1/8W, AA, TP, 1.8X	
R928	2004-001104	31018-177-563	R- METAL	56KOHM, 5%, 1/8W, AA, TP, 1.8X	
R929	2001-000429	31018-177-102	R-CARBON	1KOHM, 5%, 1/8W, AA, TP, 1.8X	
R930	2001-000429	31018-177-102	R-CARBON	1KOHM, 5%, 1/8W, AA, TP, 1.8X	
R931	2001-000563	31018-177-273	R-CARBON	27KOHM, 5%, 1/8W, AA, TP, 1.8X	
R932	2001-001062	31018-377-106	R-CARBON(S)	10MOHM, 5%, 1/2W, AA, TP, 2.4X	
R933	2001-000290	31018-177-103	R-CARBON	10KOHM, 5%, 1/8W, AA, TP, 1.8X	
R934	2001-001092	31018-377-109	R-CARBON(S)	1OHM, 5%, 1/2W, AB, TP, 2.4X6	
R935	2001-000273	31018-177-104	R-CARBON	100KOHM, 5%, 1/8W, AA, TP, 1.8	
R936	2001-000548	31018-177-274	R-CARBON	270KOHM, 5%, 1/8W, AA, TP, 1.8	
R937	2004-001140	31018-177-682	R- METAL	6.8KOHM, 5%, 1/8W, AA, TP, 1.8	
R938	2004-001140	31018-177-682	R- METAL	6.8KOHM, 5%, 1/8W, AA, TP, 1.8	
R940	2001-000429	31018-177-102	R-CARBON	1KOHM, 5%, 1/8W, AA, TP, 1.8X	
R941	2001-000613	31018-177-392	R-CARBON	3.9KOHM, 5%, 1/8W, AA, TP, 1.8	
R942	2001-000613	31018-177-392	R-CARBON	3.9KOHM, 5%, 1/8W, AA, TP, 1.8	
R943	2001-000613	31018-177-392	R-CARBON	3.9KOHM, 5%, 1/8W, AA, TP, 1.8	
R944	2001-000857	31018-177-561	R-CARBON	560OHM, 5%, 1/8W, AA, TP, 1.8X	
R945	2001-000857	31018-177-561	R-CARBON	560OHM, 5%, 1/8W, AA, TP, 1.8X	
R946	2001-000857	31018-177-561	R-CARBON	560OHM, 5%, 1/8W, AA, TP, 1.8X	
R947	2001-000522	31018-177-223	R-CARBON	22KOHM, 5%, 1/8W, AA, TP, 1.8X	
R948	2001-000780	31018-177-471	R-CARBON	470OHM, 5%, 1/8W, AA, TP, 1.8X	
R949	2001-000008	31018-177-153	R-CARBON	15KOHM, 5%, 1/8W, AA, TP, 1.8X	
R950	2001-000290	31018-177-103	R-CARBON	10KOHM, 5%, 1/8W, AA, TP, 1.8X	
R951	2001-000613	31018-177-392	R-CARBON	3.9KOHM, 5%, 1/8W, AA, TP, 1.8	
R952	2001-000472	31018-177-272	R-CARBON	2.7KOHM, 5%, 1/8W, AA, TP, 1.8	
R953	2001-000290	31018-177-103	R-CARBON	10KOHM, 5%, 1/8W, AA, TP, 1.8X	
R954	2001-000290	31018-177-103	R-CARBON	10KOHM, 5%, 1/8W, AA, TP, 1.8X	
R955	2001-000290	31018-177-103	R-CARBON	10KOHM, 5%, 1/8W, AA, TP, 1.8X	
R956	2001-000003	31018-177-331	R-CARBON	330OHM, 5%, 1/8W, AA, TP, 1.8X	
R957	2001-001181	31018-377-680	R-CARBON(S)	68OHM, 5%, 1/2W, AB, TP, 2.4X6	
R958	2001-000241	31018-177-152	R-CARBON	1.5KOHM, 5%, 1/8W, AA, TP, 1.8	
R959	2001-000290	31018-177-103	R-CARBON	10KOHM, 5%, 1/8W, AA, TP, 1.8X	
R960	2001-000281	31018-177-101	R-CARBON	100OHM, 5%, 1/8W, AA, TP, 1.8X	
R961	2001-000290	31018-177-103	R-CARBON	10KOHM, 5%, 1/8W, AA, TP, 1.8X	
R962	2001-001181	31018-377-680	R-CARBON(S)	68OHM, 5%, 1/2W, AB, TP, 2.4X6	
R963	31018-377-102		R-CARBON/METAL FILM	RD 1/2T 1K-J	
R964	31018-377-102		R-CARBON/METAL FILM	AD 1/2T 1K-J	
R965	31018-377-102		R-CARBON/METAL FILM	RD 1/2T 1K-J	

Loc No	New Code No	Old Code No	Description	Specification	Remarks
R966	31018-377-102		R-CARBON/METAL FILM	RD 1/2T 1K-J	
R967	2001-000832	31018-177-511	R-CARBON	510OHM,5%,1/8W,AA,TP,1.8X	
R981	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X	
A982	2001-000429	31018-177-102	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X	
⚠ AL801	3501-000285	34729-004-010	RELAY-POWER	12V,-,10A,-,15MS,5MS	
⚠ RW01	31028-328-472		R-COMPOSITION	AC 1/2T 4.7K-K/ERC-12GL 4	
⚠ RW02	31028-328-472		R-COMPOSITION	RC 1/2T 4.7K-K/ERC-12GL 4	
⚠ RU01	31028-328-185		R-COMPOSITION	RC 1/2T 1.8M-K/ERC-12GL 1	
RU02	2001-000780	31018-177-471	R-CARBON	470OHM,5%,1/8W,AA,TP,1.8X	
RW01	2001-000273	31018-177-104	R-CARBON	100KOHM,5%,1/8W,AA,TP,1.8	
Ri vo2	2001-000273	31018-177-104	R-CARBON	100KOHM,5%,1/8W,AA,TP,1.8	
RW03	2001-000273	31018-177-104	R-CARBON	100KOHM,5%,1/8W,AA,TP,1.8	
RW04	2001-000273	31018-177-104	R-CARBON	100KOHM,5%,1/8W,AA,TP,1.8	
RW05	2001-000281	31018-177-101	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X	
RW06	2001-000273	31018-177-104	R-CARBON	100KOHM,5%,1/8W,AA,TP,1.8	
RW07	2004-001213	31018-177-752	R-METAL	7.5KOHM,5%,1/8W,AA,TP,1.8	
RW08	2001-000837	31018-177-513	R-CARBON	51KOHM,5%,1/8W,AA,TP,1.8X	
RW09	2001-001096	31018-377-229	R-CARBON(S)	2.2OHM,5%,1/2W,AA,TP,2.4X	
RW10	2001-001096	31018-377-229	R-CARBON(S)	2.2OHM,5%,1/2W,AA,TP,2.4X	
RX01	2001-000397	31018-177-184	R-CARBON	180KOHM,5%,1/8W,AA,TP,1.8	
RX02	2001-000411	31018-177-183	R-CARBON	18KOHM,5%,1/8W,AA,TP,1.8X	
⚠ RX03	2004-001397	A1006-0741	R-METAL(S)	4.7KOHM,1%,1/2W,AA,TP,2.4	
⚠ RX04	2004-001376	A1006-0739	R-METAL(S)	11KOHM,1%,1/2W,AA,TP,2.4X	
RX05	2001-000522	31018-177-223	R-CARBON	22KOHM,5%,1/8W,AA,TP,1.8X	
RX08	2001-000837	31018-177-513	R-CARBON	51KOHM,5%,1/8W,AA,TP,1.8X	
SF101	2904-000287	B1245-0052	FILTER-SAW AV	45.75MHZ,S1P5P,ST	
SFK01	2904-000289	B1245-0045	FILTER-SAW AV	45.75MHZ,S1P5P,ST	
⚠ T401	AA26-50001B	32846-070-007	HORIZ.DRIVE	-,7.1MH,102UH,10-20UH,YLQ	
⚠ T444	AA26-30002T	A1201-0059	TRANS-FRYBACK	-,FCK-14B044,14*,125V	
⚠ T801	AA26-20004D	A1206-0095	TRANS-SWITCHING	-,80-260V,-,ER424215,630U	
⚠ TU01	AA40-10005A		TUNER-F/S	-,TECC1880PK25B,NTSC/USA,	
us0075	AA68-50067A	34503-0100-000	LABEL-RATING	T/P 90(G),T0.2,-,-,-,AL	
⚠ V999	3704-000102	A3047-0021	SOCKET-CRT	10P,22.5PI,14.3PI,SM	
x201	2801-000226	34537-001-002	CRYSTAL-UNIT	3.579545MHZ,20PPM,28-AAM	
x202	2802-000172	34539-300-005	RESONATOR-CERAMIC	503.5KHZ,0.5%,BK,7.0X3.5X	
⚠ X901	81280-0219		CRYSTAL	32.768KHZ P3 20PPM	
2201	34527-460-001		FILTER-CERAMIC	TPS4.5MCTF21	
Z601	2903-000135	81243-0071	FILTER-CERAMIC	BP,4.5MHZ	
			ASSY-H/S,VERT		
⚠ IC301	● AA96-60020A 32119-102-300	● 3182-00016-010	ASSY-H/S,VERT IC	VERT,AA62-30033A,KA2131,- KA 2131	CKD S. N. A
			ASSY-H/S,VERT		
⚠ IC401	●  32159-210-040	● 3Y82-20068-010	ASSY-H/S,VERT TR-POWER	VERT,AA62-30033A,KSD5071, KSD5071YD,NPN,1500V,800V	CKD S. N. A
			ASSY-H/S,SOUND		
⚠ IC501	●  B4012-0359		ASSY-H/S,SOUND IC-LINEAR	-,AA62-30027A,TDA6103Q,SM TDA6103Q SIP 9P VIDEO	CUD S. N. A
			ASSY-H/S,SOUND		
⚠ IC601	●  1201-000484	B4012-0418	ASSY-H/S,SOUND IC-POWER AMP	-,AA62-30004P,TDA7266,SMX 7266,ZIP,15P,-,DUAL,-,PLA	CKD S. N. A
			ASSY-H/S,POWER		
	AA96-60364A		ASSY-H/S,POWER	-,AA62-30004D,STRS6707 CO	CKD S. N. A

Loc No	New Code No	Old Code No	Description	Specification	Remarks
△ IC801	AA13-20002H	B4010-0034	IC-HYBRID	- ,STRS6707,SIP,9P,SMPS CO	
			ASSY-H/S.TR		
△ D810	•AA96-60365A B4102-0087		ASSY-H/S,TR DIODE-FR	- ,AA62-30013D,FML-G22S,SM FML-G22SI 200V 10A 40NS	CKD S. N. A
			ASSY-H/S.SOUND		
△ ICW02	• AA96-60367A B4012-0586		ASSY-H/S,SOUND IC-LINEAR	- ,AA62-30004H,TDA7240A,SM TDA7240AI ZIP BULKI POWER-AI	CKD S. N. A
			ASSY-H/S.POWER		
△ IC802	• AA96-60368A A4008-1236		ASSY-H/S,POWER IC-S/W REGU	- ,31124-0047-000,KA7631,S KA7631 SIP 10PI BULKI 5.1V/	CKD S. N. A
			ASSY-H/S.TR		
△ IC452	•AA96-60395A 1203-000243	A4008-0178	ASSY-H/S,TR IC-POS1.FIXED REG.	- ,AA62-30012B,KA7812,SMX 7812,TO-220,3P,- ,PLASTIC,I	CUD S. N. A
			ASSY-ACCESSORY		
MACH/TT	AA26-90001F	32759-115-050	TRANS-MATCHING	- ,3000HM/750HM,NTSC,40-89	
ROD/ANTI	AA42-10001Q	34509-2230022	ANT-ROD	DP,4S,500MM,MT,ULI	
USER/M	AA68-10803A		MANUAL-USERS	WP120,- ,JENG.GAMEI TV,KG1	
W/CARD	AA68-40045A	A0120-2010I	CARD-WARRANTY	- ,-,L1850,WHT,SEA,SECA,W1	
			ASSY-CRT		
△ CR	AA03-10001Q	32019-400-083	CRT-COLOR	- ,A34KQV42X,*380MG,14",9Q	
△ DY	AA27-50001K	32439-21 0-090	DEFLECTON-YOKE	- ,DSE-1422FL,14"/A34KQV42	
△ CY	AA27-60001L	A1155-0004	MAGNET-CONVERGENCE	- ,NY-225,22.5MM	
SP-DY	AA63-60028A	33309-0020-000	SPACER-DY	- ,NEOPRENE,- ,BLK,VQ W12,-	
			ASSY-PC&CONTROL		
	• AA97-80003A		ASSY-PCB,CONTROL	- ,KG1,GXE1395,SMX,SEA	
PCB	AA41-10415A	36029-0411-000	PCB-CONTROL	KG1,1,FR-1,207X38X1.6T	BARE PCB
CC01	2401-001495	31607-401-460	C-AL	47UF,20%,16V,GP,5X11MM,5M	
CNC01	AA39-20068B	36434-0008-010	LEAD-CONNECTOR,ASSY	- ,YBNH025-08,67096-008,8PI	
LDC01	0601-000368	32309-110-002	LED	ROUND,GRN,3MM,570NM	
LOC02	0601-000368	32309-110-002	LED	ROUND,GRN,3MM,570NM	
LDC03	0601-000385	32309-110-001	LED	ROUND,RED,3MM,700NM	
POWER	AA64-40256A	34164-0082-000	INDICATOR-LED,PI	- ,ABS,HB,- ,-,3374G,-	
RC01	2004-001291	31018-177-821	R-METAL	8200HM,5%,1/8W,AA,TP,1.8X	
RC02	2001-000232	31018-177-132	R-CARBON	1.3KOHM,5%,1/8W,AA,TP,1.8	
AC03	2001-000232	31018-177-132	R-CARBON	1.3KOHM,5%,1/8W,AA,TP,1.8	
RC04	2001-000800	31018-177-512	R-CARBON	5.1KOHM,5%,1/8W,AA,TP,1.8	
RC05	2004-001291	31018-177-821	R-METAL	8200HM,5%,1/8W,AA,TP,1.8X	
RC06	2001-000793	31018-177-470	R-CARBON	470HM,5%,1/8W,AA,TP,1.8X	
PMC01	AA59-60002B	A1294-0063	MODULE-REMOCON	- ,CRC-50HF,38KHZ,940MM,ME	
SU/WOO	AA64-40257A	34164-0083-000	INDICATOR-LED, S	- ,ABS,HB,- ,-,3374G,-	
SWC01	3404-000176	33609-101-003	SWITCH-TACT	12V,50MA,90-150GF,6X6MM,S	
SWC02	3404-000176	33609-101-003	SWITCH-TACT	12V,50MA,90-150GF,6X6MM,S	
SWC03	3404-000176	33609-101-003	SWITCH-TACT	12V,50MA,90-150GF,6X6MM,S	
SWC04	3404-000176	33609-101-003	SWITCH-TACT	12V,50MA,90-150GF,6X6MM,S	
SWC05	3404-000176	33609-101-003	SWITCH-TACT	12V,50MA,90-150GF,6X6MM,S	
SWC06	3404-000176	33609-101-003	SWITCH-TACT	12V,50MA,90-150GF,6X6MM,S	

Loc No	New Code No	Old Code No	Description	Specification	Remarks
SWC07I	3404-000176	33609-101-003	SWITCH-TACT	12V,50MA,90-150GF,6X6MM,S	
			ASSY-PCB,F/AV		
	● AA97-90003A		ASSY-PCB,F/AV	DP,GXE1395/UCX,KG1,-,-,-	
PCB	AA41-10444A	36029-0518-000	PCB-HEADPHONE	PH1.1,FR-1,49.5X23X1.6T	BARE PCB
CE60	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
CE61	2401-000480	31607-402-250	C-AL	10UF,20%,50V,GP,5X11MM,5M	
CN602B	AA39-20055D		LEAD CONNECTOR-ASSY	-.YBNH025-06,67096-006,6P	
JE60	3722-000143	33339-521-070	JACK-PHONE	1P,3.4MM,-,MBAG	
RE60	2001-001077	31018-377-151	R-CARBON(S)	1500HM,5%,1/2W,AA,TP,2.4X	
RE61	2001-001077	31018-377-151	R-CARBON(S)	1500HM,5%,1/2W,AA,TP,2.4X	
			ASSY-HOLDER,SPK		
	●AA92-80101A		ASSY-HOLDER,SPK	DP,ABS,V0,WP100016R5W,T1L	
HINGE,R	AA61-40050A	33093-0015-000	HINGE-ASSY, R	-.ZUD0BF,-,-,-,3374G	
HINGE,L	AA61-40051A	33093-0016-000	HINGE-ASSY, L	-.ZUD0BF,-,-,-,3374G	
GR1/W,R	AA63-50198A	34003-0096-000	GRILLE-WOOFER,R	-.SECC,-,T0.5,-,-,3374G	
GR1/W,L	AA63-50199A	34003-0097-000	GRILLE-WOOFER,L	-.SECC,-,T0.5,-,-,3374G	
BADGE	AA64-70002A	34533-0045-062	BADGE-BRAND	-.AL,-,L59,SIL,R2000	SING
			ASSY-HOLDER,SPK		
	● AA92-80102A		ASSY-HOLDER,SPK	DP,PP,V0,4R20W,CKD	
BADGE	AA64-70002A	34533-0045-062	BADGE-BRAND	-.AL,-,L59,SIL,R2000	SING
			ASSY-CABINET		
	● AA92-30155A		ASSY-CABINET,FRONT	GXE1395/UCX	
PC+CF	6002-000507	37148-530-121	SCREW-TAPPING	RH,+,2,M3,L12,ZPC(YEL),SW	
CB+2RF	6002-000514	37148-540-153	SCREW-TAPPING	RH,+,2,M4,L15,ZPC(BLK),SW	
CB+CF	6002-000514	37148-540-153	SCREW-TAPPING	RH,+,2,M4,L15,ZPC(BLK),SW	
CB+RCA	6002-000514	37148-540-153	SCREW-TAPPING	RH,+,2,M4,L15,ZPC(BLK),SW	
CF+HL	6002-000514	37148-540-153	SCREW-TAPPING	RH,+,2,M4,L15,ZPC(BLK),SW	
CF+HFI	6002-000514	37148-540-153	SCREW-TAPPING	RH,+,2,M4,L15,ZPC(BLK),SW	
LB+CA	6002-000514	37148-540-153	SCREW-TAPPING	RH,+,2,M4,L15,ZPC(BLK),SW	
TC+CB	6002-000514	37148-540-153	SCREW-TAPPING	RH,+,2,M4,L15,ZPC(BLK),SW	
PH+CF	AA60-10002A	37144-001-210	SCREW-TAPPING	-.RH,+,M4,L12,ZPC(YEL)	OD
CRT+CF	AA60-10017A	37124-100-830	SCREW-ASSY	-.WC,RH,+,M5,L35,SWRCH18A	
CABBAG	AA63-60002F	36844-115-130	SPACER-FELT	-.FELT,T0.35,-,330X15,-	
BACK/C	AA64-30916A		CABINET-BACK	DP,V0,-,-,-,AA64-30701A	
IN-BACK	AA64-60357A		INLAY-BACK	-.PS SHEET,T0.3,-,BLK,-,3	
C/CORD	AA65-30008A	36633-101-610	CLAMP-CORD	-.PE,HB,BLK,-,-	
CLMP/W	AA65-30010A	36634-111-010	CLAMP-WIRE	-.NYLON-66,V0,NTR,-,-	
CLMP,D	AA65-30016A	36635-001-910	CLAMP-D,COLL	-.NYLON,V0,NTR,DADH-360	1
BS+CF	6002-000514	37148-540-153	SCREW-TAPPING	RH,+,2,M4,L15,ZPC(BLK),SW	
STAND/B	AA61-10362A		BRACKET-STAND	-.SECC,-,T1.6,BLK,-,3374G	
STOPPCB	AA61-40053A	33383-0004-000	STOPPER-PCB	-.HIPS,HB,-,WHT,ALL MODEL	
SPRG-CSI	AA61-60003U	36674-142-920	SPRING-CS	-.SUS304,0.4,OD5.5,H12	
SPACER	AA63-60104A		SPACER-COVER	-.PVC SHEET,T0.8,BLK,-,33	
KNOPOW	AA64-10363A	34083-0242-000	KNOB-POWER	-.ABS,HB,BLK,-,3374G	
KNOMENU	AA64-10364A	34083-0244-000	KNOB-MENU	-.ABS,HB,BLK,-,3374G	
KNOCON	AA64-10616A		KNOB-CONTROL	1-P,-,-,-,AA64-10361A,3374	
FRONT/C	AA64-30917A		CABINET-FRONT	DP,HIPS,V0,-,-,BLK,WP1000	
WIN/RE	AA64-40253A	34073-0108-000	WINDOW-REMOCON	-.ABS,HB,-,-,3374G,-	
LEG/B	AA64-80020A	33003-0013-000	LEG-BOTTOM	-.HIPS,V0,-,BLK,-,3374G	

Loc No	New Code No	Old Code No	Description	Specification	Remarks
			COVER-TOP.ASSY		
	● AA63-30154A		COVER-TOP, ASSY	DP, -, -, -, -, -, AA63-30105A, ↓	
GRI/W	AA63-50200A	34003-0119-000	GRILLE-WOOFER, T	-, SECC, -, T0.5, -, PA110, 337	
TOP/C	AA64-30698A	32001-0249-000	CABINET-TOP	-, HIPS, V0, -, BLK, -, 3374G, ↓	
			ASSY-STAND		
	●AA91-70055A		ASSY- STAND	DP, -, AA91-70054A, 3374G	